

How To Set Up the WorkCentre 57xx for EIP

Prerequisites:

- The WorkCentre must have the latest firmware installed. You can download the firmware from the Xerox website.
- The Device must be EIP-capable.

Settings for the WorkCentre 5700 Series

You use the CentreWare Internet Services interface to the MFP to configure the device settings.

CentreWare – in website set <http://ip-mfp> (example <http://192.168.0.61>)

When accessing CentreWare Internet Services, a login page may display prompting for a username and password. If you do not know the password, contact your administrator. The default password is 1111. If the administrator encounters a problem changing the password, or forgets the password, a service call must be placed.

1. Configure **Machine Digital Certificate** by doing the following:
 - a. Click the **Index** link located in the upper-right hand corner of the page.
 - b. Click the **Custom Service Setup** Link.
 - c. On the Custom Service Setup page under the **Setup (Required)** heading, click the **Configure...** or **Edit...** button next to **HTTP (SSL)**.
 - d. Click the **Configure Machine Digital Certificate** link at the bottom of the page. (In a yellow box)
 - e. On the Machine Digital Certificate Management page, click the **Create New Certificate** button.
 - f. Under the Create New Certificate heading, select **Self Signed Certificate**.
 - g. Click the **Continue** button and fill in the required information.
 - h. Click the **Apply** button.
2. Configure **Enabled HTTP (SSL)** by doing the following:
 - a. Click the **Index** link located in the upper-right hand corner.
 - b. Click the **Custom Service Setup** link.
 - c. On the Custom Service Setup page under the **Setup (Required)** heading, click the **Configure...** or **Edit...** button next to **HTTP(SSL)**.
 - d. On the HTTP page under the **Secure HTTP (SSL)** select **Enabled**.
 - e. Click the **Save** button
3. Configure **Extensible Service Registration**. Depending on the version of software installed on the WorkCentre, follow the steps in one of the options below:

Option 1

- a. Click the **Index** link located in the upper-right hand corner of the page.
- b. Click the **Custom Service Setup** link.
- c. On the Custom Services Setup page, click the **Edit** button next to **Custom Service Registration**.
- d. Enable all of the services except Xerox Secure Access.

Note: If Xerox Secure Access is required, then enable it.

- e. Click the **Save** button.
- f. On the Custom Service Setup page, select the following checkboxes:
 - **Export Password to Custom Services**
 - **Display Custom Services Selection Button at local user interface**
 - **Enable the Custom Services Browser**.
- g. Click the **Apply** button.
- h. Under **Properties** on the left side of the page, click **Connectivity**.

- i. Click **Protocols**.
- j. Click the **WSD (Web Services for Devices)** link.
- k. On the WSD (Web Service for Devices) page, select the **Enabled** checkbox.
- l. Click the **Apply** button.

Option 2

- a. Click the **Index** link located in the upper-right hand corner of the page.
- b. Click the **Custom Service Setup** link.
- c. On the Custom Service Setup page under the **Setup (Required)** heading. Click **Configure...** or **Edit...** button next to **Extensible Service Registration**.
- d. On the HTTP Web Services page, configure the following settings:
 - **Extensible Service Registration:** Enabled
 - **Scan Template Management:** Enabled
 - **Session Data:** Enabled
 - **Scan Extension:** Enabled
 - **Device Configuration:** Enabled
 - Click the **Save** button